Asynchronous live electrooptic imaging and its application to free-running broadband signal sources

Masahiro Tsuchiya^{1a)} and Takahiro Shiozawa²

¹ National Institute of Information and Communications Technology,
4–2–1 Nukui-kitamachi, Koganei-shi, Tokyo 184–8795, Japan

² Department of Communication Network Engineering,
National Institute of Technology, Kagawa College,
551 Kohda, Takuma, Mitoyo, Kagawa 769–1192, Japan

a) mtsu@nict.go.jp

Abstract: Asynchronous operation of the live electrooptic imaging technique has been newly proposed and successfully demonstrated, which drastically untightens the severe restrictions regarding synchronization and modulation bandwidth in its conventional master-mode operations. The new operation mode is enabled by generation of an optical LO signal as a frequency-shifted replica of an RF signal to be visualized. Real-time visualizations of free-running MHz-class wide-band FM signals as well as Bluetooth waves carrying multi-Mb/s data emitted from an onboard module have been successfully demonstrated. Limiting factors for the bandwidth thus expanded by a factor of more than 10^6 have been clarified and systematically evaluated.

Keywords: live electrooptic imaging, asynchronous operation, frequency shifter, frequency modulation, Bluetooth module, radio frequency signal

Classification: Optoelectronics, Lasers and quantum electronics, Ultrafast optics, Silicon photonics, Planar lightwave circuits

References

- [1] M. Tsuchiya and T. Shiozawa: IEEE Photonics Society Newsletter **26** [6] (2012) 9.
- [2] M. Tsuchiya, K. Sasagawa, A. Kanno and T. Shiozawa: IEEE Trans. Microw. Theory Techn. **58** (2010) 3011. DOI:10.1109/TMTT.2010.2076672
- [3] LEI camera web site: <http://lei-camera.nict.go.jp/>
- [4] For example, *Ultrafast and Ultra-parallel Optoelectronics*, ed. T. Sueta and T. Okoshi (Ohmsha, Tokyo, 1995).
- [5] J. R. Janesick, T. S. Elliott, A. Dingiziam, R. A. Bredthauer, C. E. Chandler, J. A. Westphal and J. E. Gunn: Proc. SPIE **1242** (1990). DOI:10.1117/12.19452
- [6] A. El Gamal and H. El Toukhy: IEEE Circuits Devices Mag. **21** [3] (2005) 6. DOI:10.1109/MCD.2005.1438751
- [7] I. P. Christov, M. M. Murnane and H. C. Hapteyn: Phys. Rev. Lett. **78** (1997) 1251. DOI:10.1103/PhysRevLett.78.1251

- [8] P. B. Corkum and F. Krausz: Nat. Phys. **3** (2007) 381. DOI:10.1038/nphys620
- [9] J. A. Valdmanis, G. Mourou and C. W. Gable: Appl. Phys. Lett. **41** (1982) 211. DOI:10.1063/1.93485
- [10] B. H. Kolner and D. M. Bloom: IEEE J. Quantum Electron. **QE-22** (1986) 79. DOI:10.1109/JQE.1986.1072877
- [11] M. Tsuchiya and T. Shiozawa: Proc. IEEE APS/USNC-URSI (2013) 610.
- [12] M. Tsuchiya and T. Shiozawa: Appl. Phys. Express **7** (2014) 032401. DOI: 10.7567/APEX.7.032401
- [13] M. Tsuchiya and T. Shiozawa: Appl. Phys. Express **7** (2014) 062501. DOI: 10.7567/APEX.7.062501
- [14] M. Tsuchiya and T. Shiozawa: Appl. Phys. Express **6** (2013) 072602. DOI: 10.7567/APEX.6.072602
- [15] M. Tsuchiya, H. Sano and T. Shiozawa: Proc. IEEE CMA (2015) WC1.3.
- [16] M. Tsuchiya and T. Shiozawa: Dig. IEEE IMS (2012) WEPR-1.
- [17] M. Tsuchiya and T. Shiozawa: Appl. Phys. Express **8** (2015) 042502. DOI: 10.7567/APEX.8.042502
- [18] M. Tsuchiya and R. Ikeno: Proc. EuMC (2011) 389.
- [19] Hardware specifications of ZEAL-S01, ADC Technology Inc. (2010) (in Japanese).
- [20] BlueCore BlueTest3 User Guide Issue 6, CSR (2011).
- [21] Bluetooth specification v2.1 + EDR, Bluetooth SIG (2007).

1 Introduction

Since high frequency electric signals and radio waves are invisible, it is highly attractive academically and technologically to intuit their space-domain behaviors through agile visualization of their distributions and dynamics. The technique named live electrooptic imaging (LEI) [1, 2, 3] shown in Fig. 1a is unique for enabling this functionality experimentally, where electric fields in the microwave frequency range are displayed in real-time phase-evolving video formats. In the LEI system, the two ultimate properties of photonics [4], i.e., the ultra-parallel [5, 6] and ultra-fast [7, 8] natures are merged through a plate-shaped electrooptic (EO) sensor [9, 10].

While various futuristic applications of the LEI technique are expected in and around circuits and antennas as well as issues of electromagnetic interferences, demonstrated so far have been the following basics; (a) wave vector mappings [11] and their applications for high-definition wave imaging and waveguide mode analyses [12], (b) distribution visualizations of rotating electric field vectors and their ellipticity [13], (c) visualizations and decompositions of Bloch states in metamaterial structures [14], (d) visualizations of waves propagating in and around electromagnetic absorbers [15], and (e) wave packet imaging [16]. Recently, the scheme of detached EO imaging (DEI) [17] was added to the list. The present status of the LEI technique [3] is specified by its highest frequency of visualized waves, visional area, highest optical magnification ratio, and maximum pixel number, which are 100 GHz [2], 25-mm square [3], 10 [2], and $256 \times 256 = 65,536$ [18], respectively.

In this paper, a new LEI operation mode has been proposed and successfully demonstrated, which drastically untightens the conventional LEI restrictions in

synchronization and modulation bandwidth of a device-under-test (DUT). The method, i.e., the asynchronous LEI technique, has been applied to a free-running signal source of MHz-class wide-band (WB) frequency modulation (FM) as well as an onboard Bluetooth module having its own independent quartz oscillator and emitting 2.4-GHz waves carrying multi-Mb/s data. Real-time visualizations of their electric field distributions and dynamics have been successfully demonstrated. In addition, limiting factors for the bandwidth thus expanded by a factor of more than 10^6 have been clarified and systematically assessed.

Fig. 1. (a) Live electrooptic imaging setup in the asynchronous operation mode. (b) A pair of phase-locked drivers, which has been utilized for the conventional master-mode operations instead of the frequency shifter in (a). AR/HR: anti/high-reflection coated, CCD: charge-coupled-device, CMOS: complementary metal-oxide-semiconductor, DUT: device-under-test, IS: image sensor, LED: light-emitting-diode, LO: local oscillator, MZM: Mach-Zehnder modulator, RF: radio frequency.

2 System configurations

2.1 Conventional restrictions

In conventional LEI applications, there has been a major requirement that a signal at a radio frequency (RF) f_{RF} to be visualized should be synchronous with its sampling measurement at a frequency f_{IS} in the systems' fast complementary metal-oxide-semiconductor (CMOS) image sensor (IS) with no reference signal input equipped. The synchronization has been reasonably considered necessary for the stable EO imaging with a high signal-to-noise ratio (SNR) since f_{RF} is down-converted to a visible frequency δf by a factor of 10^9 or more [1].

Furthermore, its local oscillator (LO) signal, which drives a Mach-Zehnder optical modulator (MZM) in the systems' optical LO signal source (Fig. 1a) and interacts with the RF signal in the EO sensor plate, has been required to synchronize with the CMOS-IS clock (Fig. 1b) also. This is because the generation of the RF-LO difference-frequency signal at the EO mixing is needed to be phase-locked

to the CMOS-IS sampling so as to maximize the image stability and SNR and, therefore, be fixed at an intermediate frequency (IF) f_{IF} of 5 kHz. In addition, the IF bandwidth is limited by a frame rate f_{FR} of LEI video, which is typically 10 frames/s, requiring the LO signal to be a temporal replica of the RF signal within f_{FR} . This situation is expressed by the following;

$$|f_{LO}(t) - f_{RF}(t) + f_{IS}/4| \leq f_{FR}, \quad (1)$$

where $f_{LO}(t)$ and $f_{RF}(t)$ are respective instantaneous frequencies of the LO and RF signals and four samplings in an IF period lead to both acquisitions of amplitude and phase.

Because of those requirements, DUTs have been severely restricted regarding their signal sources; a DUT should accompany an externally-synchronous signal source, where CMOS-IS serves as a master to a slave, i.e., DUT. In other words, the conventional operations of the LEI system have been only in the master-mode. This situation has kept the LEI technique away from a majority of completed products and/or modules to be embedded in products. In addition, the requirement to an LO signal source given by Eq. (1) has narrowed the acceptable range of RF modulations and eventually that of RF bandwidths. Consequently, two RF synthesizers have thus far served as RF and LO signal sources as shown in Fig. 1b and their spectral widths have been set quite narrow (1 Hz or less).

2.2 A solution: frequency shifter

In order to untighten the restrictions, a frequency shifting circuit in Fig. 2 has been designed and applied to the LEI system as indicated in Fig. 1a, which provides an output signal that is a precise replica for an almost arbitrary input signal but is shifted in frequency.

The output of designed frequency shifter (FS) is led to MZM in the optical LO source so as to generate 780-nm semiconductor laser light modulated at $f_{LO}(t)$, to which the succeeding processes are the same as in the conventional. The EO plate is irradiated by the optical LO signal, where the two-dimensional (2D) EO mixing of the RF signal and the optical LO signal takes place with 2D-spatial coherence. The mixing leads to generation of optical IF modulation spatially distributed within the laser beam cross section, which is detected by CMOS-IS. The pixel signal is then temporally averaged and constructs a video frame image on a display in real time.

While the relationship in Eq. (1) is preserved, the original RF signal and the generated LO signal are asynchronous with the CMOS-IS clock, but their difference frequency signal is and carry the spatial phase relationship of the original RF signal. Stable EO imaging with a high SNR and a wide range of acceptable DUTs is enabled by this phase-locked IF component.

Respectively shown in Figs. 2a and 2b are a schematic of the FS circuit and its concept of frequency management. The RF signal of DUT is once down-converted to another intermediate frequency range IF2 around 400 MHz by the first mixer and an LO signal (LO1) at f_{LO1} . Generated unnecessary frequency components are eliminated by the IF2 band-pass filter (BPF) having a 200-MHz-wide passband with a center frequency of 400 MHz, and the BPF output is then up-converted to the

LO frequency by the second mixer and an LO signal (LO2) at f_{LO2} . Both LO1 and LO2 signals are synchronous with the CMOS-IS clock and their difference in frequency is f_{IF} . The FS bandwidth is dominated by the BPF characteristics.

Fig. 2. Schematic of frequency shifter (a) and its spectral configuration (b) together with demonstrated single-tone spectra with a downward frequency shift by 1 MHz (c). BPF: band pass filter.

An RF single sideband mixer could be an alternative to the present FS circuit. However, specifications of commercially available single sideband mixers are not satisfactory enough: the lower limit of their IF frequency is far higher than the needed (5 kHz) and their LO-RF isolations are around 30 dB that is not high enough.

The FS operation has been confirmed experimentally using an RF spectrum analyzer (HP8593) as shown in Fig. 2c; a measured set of input and output signals are apart by $f_{LO1} - f_{LO2}$, which in this particular experiment was set 1 MHz instead of the needed (5 kHz) in the LEI system owing to the limited frequency resolution of the RF spectrum analyzer (9 kHz). The insertion loss is 20 dB or lower before the power adjustment section. The f_{RF} component included in the output is below the detection limit, indicating an LO-RF isolation of 40 dB or higher. The isolation is indeed 60 dB or higher, which was evaluated in a separate RF spectral measurement with an amplifier.

3 Experiments

3.1 Basic characterization

In order to confirm the operation principle of the asynchronous LEI system, the following preliminary EO imaging experiment has been performed. A microstrip line with a gap formed on a printed circuit board material of flame-retardant type 4 was chosen as DUT, whose optical image taken through the (100) ZnTe EO plate by a charge-coupled-device (CCD) camera embedded in the setup is shown in Fig. 3b. The EO plate is sensitive to the electric field E_z in the z-direction. As shown in Fig. 3a, a single-tone 2-GHz output of an unlocked RF signal source (HP83640A) was divided into two; one was fed to FS and the other drove DUT.

A successfully acquired EO phasor image is shown in Fig. 3c, where standing wave formation due to the gap reflection appears clearly. As references, EO images obtained by the conventional master-mode operations (Fig. 1b) with and without

the reference signal to the RF signal source are shown in Fig. 3d and 3e, respectively. The former is quite similar to Fig. 3c while the EO image disappears in the latter. These results clearly indicate the asynchronous operation does work efficiently for a free-running signal source.

Fig. 3. Basic characterization of the asynchronous LEI system has been performed using a gaped microstrip line (MSL) sample as DUT. (a) Experimental setup around the frequency shifter in Fig. 2. (b) A CCD image of the MSL taken through the EO plate. Results of EO imaging in the asynchronous operation mode (c) and by the conventional master-mode operation with (d) and without (e) the RF synchronization with the CMOS-IS. RF spectra of a 2-GHz signal frequency-modulated by a 1- V_{pp} 1-MHz signal with a 10-MHz/V sensitivity (f), and its imaging result obtained in the asynchronous operation mode (g).

In order to clarify the high bandwidth nature of the present method, visualization of an asynchronous WB-FM signal has been performed. The WB-FM signal was generated by injecting a sinusoidal signal having amplitude of 1 V_{pp} and a frequency f_s of 1 MHz to the RF signal source with an FM sensitivity of 10 MHz/V, whose measured spectra are shown in Fig. 3f. The visualization result is shown in Fig. 3g, indicating that the bandwidth of the present LEI system is high enough to have a 10-MHz class WB-FM signal visualized. The degradation of the image quality in Fig. 3g is discussed below.

3.2 Visualization of RF waves for an onboard Bluetooth module

In order to demonstrate the expanded DUT acceptability, 2.4-GHz waves emitted from a commercially available onboard Bluetooth module (ZEAL-S01 [19], ADC technology Inc.) have been tried to visualize. A picture of the module is at the right-bottom corner of Fig. 1a while its front and side views are in Figs. 4a and 4b, respectively. A chip antenna (TDK ANT8030-2R4-01A) was originally mounted on the module board, to which a universal-serial-bus interface board in the left-hand side of Fig. 4b was attached for its external operation control. Shown in Fig. 4a is a schematic around FS, where the RF emission from the chip antenna is received by a rod antenna and fed to FS. The EO plate was set just on the top of the module, through which an optical image was taken as shown in Fig. 4c. The two printed circuit boards as well as the chip antenna appear clearly in the optical image.

The first module experiment was performed in an operation test mode [20] that enables the transmitter in continuous transmission at a designated frequency

(2.444 GHz). The receiver was not operating. Respective distributions of E_z magnitude, phase, and phasor for the emitted wave were successfully and simultaneously visualized as shown in Figs. 4d, 4e and 4f. In Fig. 4d, the amplitude distribution in dB is overlaid on the CCD image in Fig. 4c, indicating that the origin of the wave emission is off the center of the antenna but at its edge: the upper end of the antenna image in Fig. 4c. Figs. 4e and 4f shows phase and phasor video images stroboscopically with a phase interval of $\pi/6$. The phase data in the videos are doubled for the sake of higher visibility of the wave behaviors via halved wavelengths therein. The behaviors of wave front and wave power are clearly visualized, which can be more clearly recognized in the corresponding movies embedded in the central regions of Figs. 4e and 4f.

Fig. 4. Visualization setup for RF waves emitted from an onboard Bluetooth module (a) together with its side view photograph (b). (c) A top-view CCD image taken through the EO plate placed on the module top for the following EO video images; a magnitude image (d) and stroboscopic image series for phase (e) and phasor (f). In (e) and (f), the phase data at each pixel is doubled for clearer wave visibility via halved wavelengths.

In the second module experiment, the transmitter was operated with a fixed carrier frequency (2.444 GHz) and payload of PRBS9 data. While various types of packets was tried, the representative was 3-DH5 [20] of the enhanced data rate [21] having its maximum payload size of 1021 information bytes and 5 occupied time slots, which provides the highest bit rate in Bluetooth ver. 2.1. LEI video images with similar qualities and a little less image signal power with respect to those in Fig. 4 were successfully obtained, indicating that the bandwidth of the present method provides visualization of radio waves carrying Mb/s-class data. EO images for other types of Bluetooth packets were also obtained successfully.

In the third module experiment, the transmitter was operated with a simplified frequency hop (FH) sequence designated by the country code 0 [21] and the same packet types as in the above. Unfortunately enough, the EO image of the 2.4 GHz radio wave disappeared by the FH addition, whose cause is discussed below.

4 Discussions

4.1 Ghost images

One of the key issues in the present method is the LO-RF isolation at the FS output. If this value is insufficient, the optical LO signal contains a certain amount of RF signal power in advance of the interaction between the EO plate and RF signal to be visualized, and consequently an unnecessary IF signal is added in the CMOS-IS photo-detection process. The result is a uniform ghost EO image on the display.

Furthermore, pairs of spurious signals at $kf_{\text{RF}} + lf_{\text{LO1}} + mf_{\text{LO2}}$, where k , m , and n are integer, generated at the FS mixers or thereafter could lead to ghost images as well. For example, beats between such components as $(k, l, m) = (4, -5, 1)$ and $(4, -4, 0)$ generate signals at f_{IF} .

Therefore, enhancement of the LO-RF isolation and suppression of the spurious signals should be accomplished in future asynchronous LEI systems for their better performances.

4.2 Bandwidth limitation

It should be noted that there exists a detour of the LO signal and consequently a time delay τ of the LO signal arrival at the EO plate is generated with respect to the RF signal to be visualized. The delay consists of traveling time over the electrical and optical paths from the RF signal source via FS and MZM to the EO plate as well as electrical circuit delay in FS, which is estimated in total at 30 ns or longer. Effects of the time delay would be two-fold as follows.

The one is intolerable deviation of instantaneous difference frequency $f_{\text{RF}}(t) - f_{\text{LO}}(t - \tau)$ from f_{IF} . This is typical for such a single-carrier RF signal as the WB-FM signal in the above, whose instantaneous frequency is highly varied by the modulation. The degradation of the image signal in Fig. 3g can be attributed to this effect. The situation of FSK signals is similar, where the temporal RF-LO overlap having the fixed f_{IF} within a symbol information byte is reduced by the delay. The slight degradation of the image signal for the 3-DH5 packet of the Bluetooth module can be ascribed to the effect.

The second effect of the delay is caused in multiple-carrier cases such as the Bluetooth FH and may have made the video image disappear. Since phase delay of LO signal at each Bluetooth channel differs from others, the phase of IF signal varies randomly by packets, which results in mutual cancelation during the IF signal averaging for the construction of a video frame.

More detailed and quantitative analyses of the delay effects are described below.

4.3 Theoretical evaluations of the delay effects

Let an RF signal $F(t)$ having a carrier frequency f_{RF} (fixed) and a phase ϕ_{RF} , and its corresponding FS-generated LO signal $G(t)$ at f_{LO} (fixed) be expressed as follows;

$$F(t) = h(t) \exp(i2\pi f_{\text{RF}}t + i\phi_{\text{RF}}), \text{ and} \quad (2)$$

$$G(t) = ah(t - \tau) \exp(i2\pi f_{\text{LO}}(t - \tau) + i\phi_{\text{RF}}), \quad (3)$$

respectively, where $h(t)$ represents a modulation format of the RF signal and a expresses the total amplitude variation from the RF signal to the LO signal. A CMOS-IS pixel detects a down-converted result of the EO mixing of Eqs. (2) and (3), whose time-averaged amplitude is given by

$$\text{Re}[\int_0^T dt \{ah(t)h^*(t - \tau)\}/2T], \quad (4)$$

where the time period for the averaging integral is given by $T = 1/f_{\text{FR}}$.

As for an FM signal having an amplitude A , a maximum frequency shift Δf , and a modulation frequency f_s , Eq. (4) is given by

$$= aA^2 J_0(2\Delta f \sin(\pi f_s \tau)/f_s)/2, \quad (5)$$

where J_0 is the 0-th order Bessel function. Eq. (5) for f_s of 1 MHz is plotted as functions of τ and Δf in Figs. 5a and 5b, respectively. Its dependences on τ and Δf indicate that the asynchronous LEI video acquisition is limited by the product $\tau\Delta f$. The solid circles in Fig. 5b are amplitudes of experimentally derived LEI video signals, suggesting τ around 40 ns, which is in a fairly good agreement with the estimation in the above.

Fig. 5. Plotted are normalized time-averaged IF amplitudes calculated for FM signals as functions of delay (a) and maximum frequency shift Δf (b) as well as for Bluetooth packets with and without the frequency hopping (FH) (c). Solid circles in (b) are results of LEI experiments for the FM signals.

As for the Bluetooth signal with FH having a temporal length of a symbol byte T_s , and the channel interval Δf_0 in frequency (1 MHz), Eq. (4) is approximated by

$$\approx (T_s - \tau)/2T_s \times \text{Re}[\sum_{n=1}^{79} \exp(i2\pi n\Delta f_0\tau)], \quad (6)$$

where n is the channel number [20] and randomness of FH is assumed. Regarding the case without FH, Eq. (4) is given by

$$\approx (T_s - \tau)/2T_s, \quad (7)$$

where τ/T_s is a limiting factor. Plotted in Fig. 5c are Eqs. (6) and (7), which are in a fairly good agreement with the experimental results mentioned above, where the appearance of the EO images for the Bluetooth signals was dominated by FH.

5 Conclusion

The asynchronous operations of live electrooptic imaging technique have been proposed and demonstrated for the first time, where the conventional severe restrictions in synchronization and modulation bandwidth have been drastically untightened. For the asynchronous operation mode, a frequency shifter was designed and adapted to the LEI system. Real-time visualizations of free-running MHz-class WB-FM signals as well as 2.4-GHz Bluetooth waves carrying multi-Mb/s data emitted from an onboard module have been successfully demonstrated. Limiting factors for the bandwidth thus expanded have been clarified and systematically evaluated.

Necessary improvements for better performance of the asynchronous operation mode LEI technique have been pointed out; a frequency shifter with enhanced LO-RF isolation and suppressed spurious generation as well as suppression of the delay effects.

Acknowledgments

The authors have appreciated the measurement support given by Mr. Y. Shinohara and the heartwarming encouragement by Prof. J. Hamasaki. T. Shiozawa thanks Prof. H. Isshiki and Mr. M. Ohata for their helping hands.