Study on Comb-Line Filters with Coupling Windows on the Grounding Conductor

Kenichiro Kikuchi* Member Toshiaki Kitamura* Member
Yasushi Horii** Non-member Masahiro Geshiro* Non-member

This paper proposes a new type of multi-stratified comb-line filters of narrow pass band utilizing conductor-backed coplanar waveguides. It is shown through numerical simulations by means of FD-TD method that the filtering characteristics can be controlled effectively by introducing a grounding conductor with a window between the coupled two resonators. It is demonstrated that, by changing the dimensions of the window on the grounding conductor, we can change, without affecting the odd mode, the input susceptance of the even mode independently and that we can adjust the frequency of attenuation pole. An interesting feature of this filter is that an additional window on the grounding conductor makes another attenuation pole appear around the passband.

Keywords: Comb-line Filter, Attenuation Pole, FD-TD method, Conductor-Backed CPW

1. Introduction

Cellular phones are usually equipped with comb-line filters, which have an advantage that the frequency characteristics around the pass band can be greatly improved by attenuation poles^{(1), (2)}. Besides comb-line filters, some other types of filters which have attenuation poles around the passband have been proposed so far^{(3)–(7)}. Attenuation poles play a significant role not only to compress the transmission level of the stopband, but also to sharpen the passband response. Utilizing the conductor-backed coplanar waveguide (CPW), we have already proposed a dual-plane comb-line filter, which consists of two quarter-wavelength resonators placed face-to-face beyond the substrate^{(8), (9)}. The structure is suitable for miniaturization by utilizing stratifying technology. In addition, attenuation poles can easily be created just around the passband for this structure.

In this paper, we newly propose a 3-layer CPW comb-line filter. This filter has a quarter-wavelength resonator on each of the top and bottom planes and a window on the middle plane which the two resonators are coupled through. We investigate the filtering characteristics through numerical simulations by means of the FD-TD method. This filter has a benefit that an attenuation pole can be created just around the passband and it can be regulated by locating the window appropriately. Furthermore, two attenuation poles can be created just below and above the passband by opening another small window on the middle plane.

2. Comb-Line Filter with a Window on the Grounding Conductor

Figure 1 illustrates the structure of the 3-layer CPW comb-line filter that we propose in this paper. The relative permittivity of the substrate is assumed to be 10.2. The filter has two quarter-wavelength resonators each one of which is arranged on the top and bottom planes of the substrate. In this paper, we adopt simple straight resonators to clear the principle of creating attenuation poles. However, it has been confirmed that we can obtain similar characteristics when we use stepped impedance resonators (SIRs) instead of straight ones. A window is opened on the middle plane through which the two resonators are coupled to each other. Several segments of thin metal wire penetrate the substrate around the resonators to connect the metallized planes so as to remove both the parallel-plate and slot modes. The whole structure is symmetric with respect to the center axis (the dash-dotted line) in Fig.1.

The metallization pattern on the top (or bottom) plane is shown in Fig.2 in which the location of the window is also illustrated. The width of the window is fixed to be 5.0mm. For I/O ports, a finite length of CPW is connected to each resonator through an appropriate length of tapping wire.

Figure 3 illustrates flow lines of electric field of the even and odd modes of the filter shown in Fig.1.

Only the even-mode fields exist in the window region because the odd-mode fields from the top and bottom planes, which have the opposite phases, cancel each other. Therefore, the dimensions and position of the window affect only the even mode. The bandwidth of a comb-line filter is determined by the difference of resonant frequencies between the even and odd modes, and attenuation poles appear at the frequencies where

* College of Engineering, Osaka Prefecture University
1-1 Gakuen-cho, Sakai-shi, Osaka 599-8531, Japan

** Faculty of Informatics, Kansai University
2-1-1, Ryozenji-cho, Takatsuki-shi, Osaka 569-1095, Japan

Fig. 1. 3-layer CPW comb-line filter with a window on the middle plane.

Fig. 2. Metallization pattern on the top (or bottom) plane.

Fig. 3. Flow lines of electric field.

the input susceptances of both modes are equal to each other⁽⁹⁾. Consequently, designing the window appropriately, we can change the even mode alone to regulate the bandwidth and attenuation-pole frequencies of the filter.

Numerical calculations by means of the FD-TD method are carried out with a and b as parameters. Here, a and b , which determine the dimensions and position of the window, are the lengths from the terminated

Table 1. Window parameters.

pattern	a(mm)	b(mm)
1	18.5	8.5
2	16.5	8.5
3	14.5	8.5
4	18.5	12.5
5	18.5	10.5
6	18.5	8.5

(a)

(b)

Fig. 4. Frequency characteristics of scattering parameters for patterns 1, 2, and 3 in Table 1.

edge of the resonator to the upper and lower frames of the window, respectively, as shown in Fig.2. The filter is modeled on a Yee's mesh consisting of $36 \times 80 \times 110$ homogeneous cells in the FD-TD analysis; each cell size is assumed to be 0.635mm in the x direction and 0.5mm in both y and z directions. Table 1 shows several patterns of the window parameters investigated here. In this table, patterns 1-3 and 4-6 correspond to changing either a or b in Fig.2 while fixing the other parameters.

Figure 4 shows the frequency characteristics of scattering parameters for patterns 1-3 in Table 1. It is understood that by decreasing a we can lower the upper cutoff frequency of the passband without changing the lower one ; hence a very narrow passband can be achieved. This is because the even mode has the domination over the upper cutoff frequency whereas the odd mode contrariwise keeps the control over the lower cutoff frequency. It is also understood from Fig.4 that attenuation poles move toward the lower frequency region as a becomes smaller.

Fig. 8. Frequency characteristics of scattering parameters with c as a parameter when $d = 2.0\text{ mm}$: $|S_{11}|$ in (a) and $|S_{21}|$ in (b).

Fig. 9. Frequency characteristics of the input susceptances for the even and odd modes with c as a parameter.

in the frequency range below the passband. As a result, the intersection of the input susceptances between the even and odd modes, where the attenuation-pole exists, moves toward the lower frequency region as c becomes smaller.

4. Conclusions

In this paper, we have proposed a 3-layer CPW comb-line filter, which has one quarter-wavelength resonator on each of the top and bottom planes and a window on the middle plane which the two resonators are coupled through. The filtering characteristics have been investigated through numerical simulations by means of the FD-TD method. It has been shown that this filter has an attenuation pole around the passband and it can be regulated by adjusting the dimensions and location of the window. Furthermore, it has been demonstrated that two attenuation poles can be created just below and above the passband by opening another small window on the middle plane.

(Manuscript received June 10, 2002)

References

- (1) T. Ishizaki, T. Uwano, and H. Miyake: "An extended configuration of a stepped impedance comb-line filter", *IEICE Trans. Electron.*, Vol.E79-C, No.5, pp.671-678 (1996-5).
- (2) C.D. Zhao and I. Awai: "A study on vertically installed planar (VIP) combline bandpass filters via 3D-FDTD method", *IEICE Trans. Electron.*, Vol.E81-C, No.4, pp.602-607 (1998-4).
- (3) K. Wada and I. Awai: "Design of a bandpass filter with multiple attenuation poles based on tapped resonators", *IEICE Trans. Electron.*, Vol.E82-C, No.7, pp.1116-1122 (1999-7).
- (4) Y.J. Ko, J.H. Kim, and B.K. Kim: "A novel approach for the design of a bandpass filter with attenuation poles using a linear relation ship", *IEICE Trans. Electron.*, Vol.E82-C, No.7, pp.1110-1115 (1999-7).
- (5) J.T. Tsai and C.L. Huang: "Bandpass filters with multiple attenuation poles in the stopband", *IEICE Trans. Electron.*, Vol.E83-C, No.7, pp.1160-1165 (2000-7).
- (6) A.C. Kundu and I. Awai: "Control of attenuation pole frequency of a dual-mode microstrip ring resonator bandpass filter", *IEEE Trans. Microwave Theory and Tech.*, Vol.49, No.6, pp.1113-1117 (2001-7).
- (7) M. Matsuo, H. Yabuki, and M. Makimoto: "Dual-mode stepped-impedance ring resonator for bandpass filter applications", *IEEE Trans. Microwave Theory Tech.*, Vol.49, No.7, pp.1235-1240 (2001-7).
- (8) T. Kitamura, Y. Horii, M. Geshiro, and S. Sawa: "A dual-plane comb-line filter having plural attenuation poles", *IEEE Trans. Microwave Theory Tech.*, Vol.50, No.4, pp.1216-1219 (2002-4).
- (9) T. Kitamura, Y. Horii, M. Geshiro, and S. Sawa: "A dual plane comb-line filter consisting of conductor-backed coplanar waveguide", *Trans. IEE of Japan*, Vol.121-C, No.5, (2001-5).

Kenichiro Kikuchi (Student Member) was born in Kyoto, Japan, in 1977. He received the B.E. and M.E. degrees in electrical and electronic systems from Osaka Prefecture University, Sakai, Japan, in 2001 and 2003, respectively. Currently, he works in Murata Manufacturing Co., Ltd., Shiga, Japan.

Toshiaki Kitamura (Member) was born in Osaka, Japan, in 1965. He received the B.E., M.E., and Ph.D. degrees in electrical communication engineering from Osaka University, Osaka, Japan, in 1989, 1991 and 1994, respectively.

In April 1994, he joined the Department of Electrical and Electronic Systems, Osaka Prefecture University, Sakai, Japan, where he is now an Assistant Professor. He has been engaged in research and education on microwave engineering and integrated optics.

Dr. Kitamura is a member of the Institute of Electronics, Information and Communication Engineering (IEICE) and the Institute of Electrical and Electronics Engineers (IEEE).

Yasushi Horii (Non-member) was born in Shiga, Japan, in 1964. He received the B.E., M.E., and Ph.D. degrees in electrical communication engineering from Osaka University, Osaka, Japan, in 1989, 1991 and 1994, respectively.

In April 1994, he joined the Faculty of Informatics, Kansai University, Takatsuki, Japan, where he is now an Associate Professor. He has been engaged in research and education on microwave engineering.

Dr. Horii is a member of the Institute of Electronics, Information and Communication Engineering (IEICE) and the Institute of Electrical and Electronics Engineers (IEEE).

Masahiro Geshiro (Non-member) received the B.E., M.E., and Ph.D. degrees in electrical communication engineering from Osaka University, Osaka, Japan, in 1973, 1975, and 1978, respectively.

From December 1979 to March 1994, he was with the Department of Electrical and Electronic Engineering, Ehime University, Matsuyama, Japan. From March 1986 to January 1987, he was a Visiting Scholar at the University of Texas at Austin, on leave from Ehime

University. Since April 1994, he has been an Associate Professor of the Department of Electrical and Electronics Systems, Osaka Prefecture University, Sakai, Japan, where he is engaged in research and education on microwave engineering, Optical wave transmission lines and integrated optics.

Dr. Geshiro is a member of the Institute of Electronics, Information and Communication Engineering (IEICE) and the Institute of Electrical and Electronics Engineers (IEEE).