Dynamic Analysis of A New Linear Actuator Using 3-D Finite Element Method

Katsuhiro Hirata Senior Member (Osaka University, k-hirata@ams.eng.osaka-u.ac.jp)
 Yuya Hasegawa Member (Matsushita Electric Works, Ltd., hasegawa@ertc.mew.co.jp)
 Tadashi Yamaguchi Member (Gifu University, yamachu@info.gifu-u.ac.jp)
 Yoshihiro Kawase Senior Member (Gifu University, kawase@info.gifu-u.ac.jp)
 Koichi Shamoto Non-member (Gifu University, shamoto@fem.info.gifu-u.ac.jp)
 Hiroyuki Kodama Non-member (Gifu University, kodma@fem.info.gifu-u.ac.jp)

Keywords: 3-D finite element method, linear oscillatory actuator, DC motor, dynamic analysis, resonance, coupled analysis

This paper presents the dynamic analysis method for a new linear actuator using a DC motor.

Fig. 1 shows the basic construction of the actuator. It mainly consists of a DC motor, two magnets with yokes, resonance springs, shaft, and bearings. A couple of multi-polarized permanent magnets of a rotor and a linear motion armature are opposite together. The rotor is directly connected to the shaft of a DC motor, and the mover is connected to the resonance spring. The operating principle of this actuator is that the armature linearly moves in direction of z-axis as the attractive or repulsive force acts on the armature according to the rotation of the rotor. It reciprocates twice while the rotor travels around when you use a couple of four polarized permanent magnets as shown in Fig. 2.

In the proposed dynamic analysis method, the magnetic field is coupled with the equations of rotation and linear motion, and an auto-mesh modification method is developed to consider both motion.

The dynamic characteristics are computed when the rotation

speed of the rotor is varied. Table 1 shows the analyzed conditions. Fig. 3 shows the calculated time variation of the amplitude of the armature. As shown, it is found that the amplitude increases as time goes on, and it becomes stable with the amplitude of about 1.0 mm. Fig. 4 shows the characteristics of amplitude versus frequency. It is found that the amplitude of the actuator increases as the operating frequency increases because this actuator has a resonance frequency of about 240 Hz theoretically. The calculated results agree well with measured one at the frequency of 216.1 and 222.8 Hz. As the results, the validity of this method is confirmed.

Table 1. Analyzed Conditions

Magnetization of magnets (T)	1.4
Mass of armature (g)	11.55
Spring constant (N/mm)	26.3
Viscous damping coefficient (N·s/m)	0.025
Dynamic friction force (N)	2.21

Fig. 1. Basic construction of the new linear actuator

Fig. 2. Analyzed model

Fig. 3. Calculated time variation of the amplitude

Fig. 4. Characteristics of the amplitude versus frequency

Dynamic Analysis of A New Linear Actuator Using 3-D Finite Element Method

Katsuhiro Hirata*	Senior Member
Yuya Hasegawa**	Member
Tadashi Yamaguchi***	Member
Yoshihiro Kawase***	Senior Member
Koichi Shamoto***	Non-member
Hiroyuki Kodama***	Non-member

This paper presents the coupled analysis method for a new structured linear actuator that can convert the rotation into linear actuation by the attractive and repulsive force of permanent magnets. In this method, the 3-D finite element mesh modification method for multi-motion analysis is taken into consideration. The effectiveness of this method is verified through the comparison with the measured results.

Keywords: 3-D finite element method, linear oscillatory actuator, DC motor, dynamic analysis, resonance, coupled analysis

1. Introduction

Generally, the linear actuation mechanism for small sized electric and electronic equipments has been accomplished by employing movement conversion gears in conjunction with traditional rotary motor. However, this kind of movement conversion system has typically demonstrated unfavorable characteristics including significant vibration, noise, size constraints, and limitations on operating speed. As a result, alternatives to the rotary and gears model to achieve linear actuation are a topic of great interest. Then, various kinds of linear actuators have been studied⁽¹⁾⁻⁽³⁾. These actuators give a lot of advantages; high frequency, low vibration, low power consumption, size, and so on, however, they are costly as compared with the conventional mechanism.

Therefore, authors are now studying a new structured linear actuator⁽⁴⁾ that can convert the rotation into linear actuation by the attractive and repulsive force of a couple of multipolarized permanent magnets which are connected to the armature and DC motor, respectively.

In designing multi-motion actuators, it is very important to clarify the operating principle and grasp their dynamic characteristics by numerical simulation. A lot of useful analysis methods have been proposed⁽⁵⁾⁻⁽⁸⁾.

This paper presents the coupled analysis method for the new linear actuator employing the 3-D finite element method. In this analysis, the mesh modification method is employed to consider the motion of both linear actuation and rotation

at the same time. The effectiveness of this method is verified through the comparison with the measured results.

2. Analyzed Model and Condition

Fig. 1 shows the basic construction of the new structured linear actuator. It mainly consists of a DC motor, two

Fig. 1. Basic construction of the new structured linear actuator

Fig. 2. Analyzed model

* Department of Adaptive Machine Systems, Graduate School of Engineering, Osaka University
2-1, Yamadaoka, Suita, Osaka, 565-0871, Japan

** Advanced Technologies Development Laboratory, Matsushita Electric Works, Ltd.
1048, Kadoma, Osaka, 571-8686, Japan

*** Department of Information Science, Gifu University
1-1, Yanagido, Gifu, 501-1193, Japan

magnets with yokes, resonance springs, shaft, and bearings. A couple of multi-polarized permanent magnets of a rotor and a linear motion armature are opposite together with an initial gap of 1.6 mm. The rotor is directly connected to the shaft of a DC motor, and the mover is connected to the resonance spring. The operating principle of this actuator is that the armature linearly moves in direction of z-axis as the attractive or repulsive force acts on the armature according to the rotation of the rotor. Because the armature is restricted to linear motion by the sliding guide, it reciprocates twice while the rotor travels around when you use a couple of four polarized permanent magnets as shown in Fig. 2. Frequency and amplitude of this actuator can be arbitrary controlled by changing the gap, resonance spring constant, number of polarization of permanent magnets.

3. Analysis Method

3.1 Magnetic Field Analysis The fundamental equation of the magnetic field can be written using the magnetic vector potential A as follows.

$$\text{rot}(\nu \text{rot} A) = \nu_0 \text{rot} M \quad \dots\dots\dots (1)$$

where ν is the reluctivity of magnetic material, ν_0 is the reluctivity of vacuum, and M is the magnetization.

3.2 Motion Analysis The magnetic force acting on the armature is obtained using the Maxwell stress tensor method. The linear motion of the armature is given by the following equation.

Fig. 3. 3-D finite element mesh

Fig. 4. Flowchart of the analysis

$$m \frac{d^2 z}{dt^2} = F_z - F_k \mp F_s - F_c \quad \dots\dots\dots (2)$$

where m is the mass of the armature, z is the displacement of the armature, F_z is the attractive or repulsive force, F_k is the spring force, F_s is the friction force, and F_c is the viscosity resistance. F_c can be expressed by the viscous damping coefficient C as follows. Where F_s and C is obtained by the measurement.

$$F_c = C \frac{dz}{dt} \quad \dots\dots\dots (3)$$

3.3 Multi-Motion Analysis The armature linearly oscillates by the attractive and repulsive force between magnets. In this method, the rotation of the rotor and the linear motion of the armature are computed at the same time using the auto-mesh modification method, in which both methods of mesh rotation for rotation of the rotor⁽⁹⁾ and mesh movement for linear motion of the armature⁽¹⁰⁾⁽¹¹⁾ are coupled. The finite element meshes of the rotor and its surrounding air regions are rotated in the uniform angle every time step because it is supposed that the rotation speed of the rotor keeps constant. Therefore, the meshes in these regions are equally divided round the circumference of the rotor, and they are rotated by time step as shown in Fig. 3. Then, rotation angle per one step should be comparatively small (5 degree in this model). In the linear motion our re-meshing method⁽⁹⁾⁻⁽¹¹⁾ is employed so that the meshes of air gap may not be distorted according to the decrease of gap length. Time interval of the computation is decided according to the rotational speed of the rotor. Fig. 4 shows the flowchart of this analysis. The detail procedure is shown as follows:

- 1) setting the initial meshes of the rotor and armature;
- 2) mesh modification of rotor region according to the rotation angle;
- 3) computation of magnetic force on the armature by FEM;
- 4) calculation of the armature displacement by solving motion equation;
- 5) repeat the above process by the time step.

4. Results and Discussion

4.1 Comparison with Measured Results The dynamic characteristics are computed when the rotation speed of the rotor is varied, and are compared with the measured results to confirm the effectiveness of the proposed analysis

Fig. 5. Measurement System

Table 1. Analyzed Conditions

Magnetization of magnets (T)	1.4
Mass of armature (g)	11.55
Spring constant (N/mm)	26.3
Viscous dumping coefficient (N·s/m)	0.025
Dynamic friction force (N)	2.21

Fig. 6. Distribution of flux density vectors

method. Fig. 5 shows the measurement system. Table 1 shows the analyzed conditions. Fig. 6 shows the distributions of flux density vectors of rotation angle of 0, 45, and 90 degree in x-z plane when it is operated at the rotational speed of 6684.5 min^{-1} (111.4 Hz). As shown in Fig. 6, the attractive force is generated between the armature and rotor when a couple of different polarized magnets are opposite together.

Fig. 7. Time variation of the torque

Fig. 8. Time variation of the thrust

Fig. 9. Time variation of the amplitude

Conversely, the repulsive force is generated when a couple of same polarized magnets are opposite.

The armature moves twice when the rotor rotates once. Figs. 7 and 8 show the time variations of the torque and thrust of the armature when it is operated at the frequency of 222.8 Hz (rotation speed of the rotor: 111.4 Hz). From these figures, it is found that the period of the torque and thrust is 180 degrees, and they become stable after the rotor rotates seven rounds. The peak value of the torque and thrust in the positive direction is different from that in the negative direction because the gap is varied by the reciprocation of the armature. Fig. 9 shows time variation of the amplitude of the armature. As shown, it is found that the amplitude increases as time goes on, and it becomes stable with the amplitude of

Fig. 10. Characteristics of the amplitude versus frequency

Table 2. Discretization Data and CPU Time

number of element	214,272
number of nodes	38,049
number of edges	256,856
number of unknown variables	243,248
number of time steps	1081
CPU time (hours)	27.0

Computer used: Pentium 4 3.0GHz PC

Fig. 11. Characteristics of the amplitude versus rotation angle

about 1.0 mm.

Fig. 10 shows the characteristics of amplitude versus frequency. As shown, it is found that the amplitude of the actuator increases as the operating frequency increases because this actuator has a resonance frequency of about 240 Hz theoretically. However, it is impossible to evaluate the amplitude of more than 230 Hz because it reaches maximum movable range. The calculated results agree well with measured one at the frequency of 216.1 and 222.8 Hz. As the results, the validity of this method is confirmed. Table 2 shows the discretization data and CPU time.

4.2 Influence of Spring Constant on Amplitude The influence of the resonance spring constant on the amplitude is investigated by varying the spring constant at the uniform rotation speed of 6684.5 min^{-1} (111.4 Hz). Fig. 11 shows

Fig. 12. Characteristics of the amplitude versus spring constant

the comparison of calculated time variations of the amplitude with the resonance spring constant of 24 and 28 N/mm. As shown in Figs. 9 and 11, the amplitude of this actuator is amazingly influenced by the spring constant. The amplitude reaches 3.1 mm, nearly maximum movable range with the spring constant of 24 N/m while it instantly converges to about 0.6 mm with that of 28 N/mm. 40% of the amplitude drops when the spring constant increases from 26.3 to 28 N/mm (only 3.8%). Fig. 12 shows the amplitude characteristics when the spring constant is varied from 18 to 30 N/mm. It is found that the amplitude diverges with the spring constant of less than 22 N/mm, greatly drops more than 24 N/mm, and decreases very slowly more than 28 N/mm. As can be seen from these results, it is found that the suitable spring constant is around 24 N/m in order to satisfy both big amplitude and high frequency.

5. Conclusions

This paper presented the coupled analysis method for a new structured linear actuator that can convert the rotation into linear actuation by the attractive and repulsive force of permanent magnets. In this method, the 3-D finite element mesh modification method for multi-motion analysis was taken into consideration. The usefulness of this method was confirmed through the comparison with the measured results.

Moreover, the influences of the resonance spring constant on the amplitude were clarified.

(Manuscript received Jan. 26, 2006,

revised May 22, 2006)

References

- (1) Y. Hasegawa and K. Hirata: "A Study on Electromagnetic Actuator with Two-Degree-of-Freedom", *T. IEE Japan*, Vol.125, No.5, pp.519-523 (2005-5)
- (2) K. Hirata, Y. Ichii, and Y. Arikawa: "Linear Oscillatory Actuator with Dynamic Vibration Control", *T. IEE Japan*, Vol.122-D, No.4, pp.346-351 (2002-4)
- (3) T. Ota, Y. Kawase, K. Hirata, and Y. Mitsutake: "3-D Eddy Current Analysis of Linear Solenoid Using A New Auto Mesh Coupling Method", *T. IEE Japan*, Vol.119-D, No.11, pp.1393-1400 (1999-11)
- (4) T. Yamaguchi, Y. Kawase, K. Shamoto, K. Hirata, and Y. Hasegawa: "Dynamic Characteristics Analysis of New Structured Linear Actuator Using 3D-Finite Element Method", *The Papers of Tech. Meeting on Linear Drives, IEE Japan*, LD-04-74, pp.37-41 (2004)
- (5) Y. Kawase, T. Yamaguchi, M. Yoshida, and K. Hirata: "3-D Finite Element Analysis of Rotary Oscillatory Actuator Using A New Auto-Mesh Coupling Method", *IEEE Trans. on Magnetics*, Vol.37, No.5, pp.3771-3774 (2001-5)

- (6) T. Yamaguchi, Y. Kawase, H. Shiimoto, and K. Hirata: "3-D Finite Element Analysis of Dynamic Characteristics of Twin-type Electromagnetic Relay", *IEEE Trans. on Magnetics*, Vol.38, No.2, pp.361-364 (2002-2)
- (7) T. Ota, K. Hirata, T. Yamaguchi, Y. Kawase, and A. Nakase: "Dynamic Analysis Method for Multi-Motion using 3-D FEM", *T. IEE Japan*, Vol.125, No.4, pp.405-409 (2005-4)
- (8) S. Ito and Y. Kawase: Computer Aided Engineering of Electrical and Electronic Apparatus Using Finite Element Method, Morikita Publishing Co., Tokyo, Japan (2000)
- (9) Y. Kawase, T. Yamaguchi, and Y. Hayashi: "Analysis of Cogging Torque of Permanent Magnet Motor by 3-D Finite Element Method", *IEEE Trans. on Magnetics*, Vol.31, No.3, pp.2044-2047 (1995-3)
- (10) K. Hirata, Y. Hasegawa, T. Ota, T. Yamaguchi, Y. Kawase, T. Eguchi, and H. Kodama: "Dynamic Analysis of Eddy Current Damping Mechanism Employing 3-D Finite Element Method", *T. IEE Japan*, Vol.125, No.12, pp.1140-1144 (2005-12)
- (11) Y. Kawase, T. Yamaguchi, O. Miyatani, and S. Ito: "3-D Numerical Analysis of Transient Dynamic Behavior of AC Electromagnets", *T. IEE Japan*, Vol.114-B, No.1, pp.106-111 (1994-1)

Katsuhiro Hirata (Senior Member) was born in 1958. He received the B.E. degree from Osaka University in 1982 and D.E. degree from Doshisha University in 1996, respectively. He was a researcher at the R&D lab., Matsushita Electric Works Ltd. from 1982 to 2005. He joined Osaka University in 2005. He is presently an associate professor in the department of adaptive machine systems, graduate school of engineering at Osaka University. He has been engaged in research of electromagnetic applied actuators and sensors. He has received Ministry Award of Education, Science & Technology in 2003. IEEE member.

Yuya Hasegawa (Member) was born in Osaka, Japan, on December 23, 1976. He received a BS degree in 1999 and MS degree in 2001 from Doshisha University. He is presently a chief engineer at Matsushita Electric Works, Ltd., and has worked on development of electromagnetic devices.

Tadashi Yamaguchi (Member) was born in Gifu, Japan, on July 3, 1968. He received a Dr. Eng. degree from Gifu University in 1996. He was an assistant professor of electrical engineering at Chubu University in 1996, and became a lecture in 1998. He joined Gifu University in 1999. He is presently an associate professor in the department of information science at Gifu University from 2003. He had been engaged in development of numerical analysis of magnetic field and application. IEEE member.

Yoshihiro Kawase (Senior Member) was born in Gifu, Japan, on April 24, 1956. He received a MS degree from Okayama University in 1981, and a Dr. Eng. degree from Kyoto University in 1986. He was an assistant professor at Okayama University from 1981 to 1985. He joined Gifu University in 1985, and became an associate professor in 1988. He is presently a professor in the department of information science at Gifu University from 1997. He had been engaged in development of magnetic field analysis using the 3-D finite element method. IEEE member.

Koichi Shamoto

(Non-member) was born in Gifu, Japan, on February 27, 1981. He received a BS degree from Gifu University in 2003. He is presently a student of master's course at Gifu University and has studied on numerical analysis of magnetic field.

Hiroyuki Kodama

(Non-member) was born in Gifu, Japan, on January 9, 1982. He received a BS degree from Gifu University in 2003. He is presently a student of master's course at Gifu University and has studied on numerical analysis of magnetic field.