NUCLEAR REACTOR POWER CONTROL SYSTEM BASED ON FLEXIBILITY MODEL

Li Gang

*School of Nuclear Science & Technology
 Xi'an Jiaotong University
 Email: ggangli@stu.xjtu.edu.cn*

Zhao Fu-Yu *

**Li Chong
 Tai Yun**

*School of Nuclear Science & Technology
 Xi'an Jiaotong University
 Email: fyzhao@mail.xjtu.edu.cn

1. INTRODUCTION

In designing the reactor power control system, resolve both the nonlinear problem of a reactor power model and the design one of a controller to cater to the reactor based on the principle of flexibility model developed in the paper. The whole calculations and simulations are done in MATLAB.

2. DESIGNING and SIMULATING

First, according to the reactor from H.B. ROBINSON nuclear plant (Kerlin, et al., 1976), construct the linear power model from the reactivity caused by the control rod movement to the deviation of reactor power from initial steady-state value and calculate the linear power models G_1 , G_2 , G_3 , G_4 and G_5 at five power levels 90%, 70%, 50%, 30% and 10% in turn as five local models of the reactor.

Then design a controller of every local model as a local controller which consists of an optimal controller and a PID controller. Use the Optimal Controller Designer toolbox to contrive every optimal controller $G_{OCi}(i=1, \dots, 5)$ first and rapidly to avoid choosing weight matrixes Q and R in the traditional optimal control; then devise every PID controller $G_{PIDCi}(i=1, \dots, 5)$ via Genetic Algorithm to set parameters of the PID controller for further improving the dynamic performances.

Third, the principle of flexibility model proposed is to seek the unknown linear power model at a random power level via adopting the known local models $G_i(i=1, \dots, 5)$ at the five levels of the nonlinear reactor and a triangle membership function chosen. This model sought is called a flexibility model. Exploit the set of flexibility models at global levels obtained to approximate the reactor. Similarly,

get flexibility controllers at whole levels via this principle and the known local controllers $G_{PIDCi} * G_{OCi}(i=1, \dots, 5)$.

Both the flexibility model and the flexibility controller at a random power level compose a power control system at this level. The set of the power control system at every power level is to approximately carry out the power control of the nuclear reactor.

Finally, the simulation result shows that the flexibility controller of the flexibility model at a level is equally valid for the linearized power model at the level. The reference (Ziya Akcasu, et al., 1971) shows that the reactor model based on lumped parameters at a level can be approximately substituted by a linearized model at this level. So the nuclear reactor power control system based on flexibility model designed is efficient for the reactor.

3. CONCLUSION

Whole simulation results show that the idea of flexibility model is feasible; this new try of designing a local controller is rapid and effective; the nuclear reactor power control system designed is effective.

REFERENCES

- Kerlin, T.W., Katz, E.M., Thakkar, J.G., and Strange, J.E., 1976. "Theoretical and Experimental Dynamic Analysis of the H.B. Robinson Nuclear Plant". Nuclear Technology, 30(3), Sep., pp. 299-316.
- Ziya Akcasu, Lellouche Gerald, S., and Shotkin Louis, M., 1971. "Mathematics Methods in Nuclear Reactor Dynamics". Academic Press, New York, Chap. 4-7, pp: 116-450.

NUCLEAR REACTOR POWER CONTROL SYSTEM BASED ON FLEXIBILITY MODEL

Li Gang

*School of Nuclear Science & Technology
Xi'an Jiaotong University
Xi'an, Shaanxi, 710049
P. R. China
Email: ggangli@stu.xjtu.edu.cn*

Zhao Fu-Yu^{*}

Li Chong

Tai Yun

*School of Nuclear Science & Technology
Xi'an Jiaotong University
Xi'an, Shaanxi, 710049
P. R. China*

Keywords: Reactor power model Optimal controller PID controller Optimal Controller Designer
Genetic Algorithm Flexibility controller Flexibility model

ABSTRACT

Design the nuclear reactor power control system in this paper to cater to a nonlinear nuclear reactor. First, calculate linear power models at five power levels of the reactor as five local models and design controllers of the local models as local controllers. Every local controller consists of an optimal controller contrived by the toolbox of Optimal Controller Designer (OCD) and a proportion-integration-differentiation (PID) controller devised via Genetic Algorithm (GA) to set parameters of the PID controller. According to the local models and controllers, apply the principle of flexibility model developed in the paper to obtain the flexibility model and the flexibility controller at every power level. Second, the flexibility model and the flexibility controller at a level structure the power control system of this level. The set of the whole power control systems corresponding to global power levels is to

approximately carry out the power control of the reactor. Finally, the nuclear reactor power control system is simulated. The simulation result shows that the idea of flexibility model is feasible and the nuclear reactor power control system is effective.

1. INTRODUCTION

Nuclear reactors have the characteristics of nonlinearity and their parameters vary according to the power level, so nuclear reactors are nonlinear time-dependent systems. Functions of a nuclear reactor power control system are to guarantee that the nuclear reactor can work steadily and to meet the whole performance requirements. Given a nonlinear time-dependent system in this paper, there are two problems to be handled during the design of the power control system of a reactor. They are both how to deal with the nonlinear model of the reactor and how to design the control system which can adapt the whole power levels by applying an advanced control strategy.

The reactor power model modeled is a linear time invariant (LTI) model, the input is the reactivity caused by

^{*}Address: Phone.: +086-029-82668648;
Fax: +086-029-82667802;
Email: fyzhao@mail.xjtu.edu.cn

the control rod movement and the output is the deviation of reactor power from initial steady-state value. LTI models at five power levels are treated as five local models of the reactor. Resolve the problem of the reactor nonlinearity by utilizing these local models and the idea of flexibility model to approximately substitute the reactor power model.

During designing a local controller of every local model, the combination control strategy of the optimal control and the PID control is utilized. The optimal control has been used for nuclear reactors with improved temperature performances (Adel Ben-Abdenour, et al., 1992). However, the traditional optimal control problem is usually resolved by choosing two appropriate weighting matrixes, namely Q and R . At present, the parameters of the two matrixes are only selected and regulated subjectively according to a practical situation. This process increases computation load and the solving difficulty. So use OCD to contrive every optimal controller to avoid selecting Q and R . Robustness, reliability and being apt to be carried out in practice are merits of the PID control, so it is one of the most extensive strategies used in the industry control field (Bennett, 1993). The effect of the PID control depends on parameters setting of PID. Researching technologies about parameters setting is meaningful. At present, there are many methods of setting PID parameters, such as the indirect optimizing method, the gradient method, the climbing method etc. In thermal systems, the simplex method and the expert method are used widely. Though these methods have the good characteristic of optimizing, some drawbacks do exist. The simplex method is sensitive to an initial value and is apt to fall into the optimum solution partly; too much experience is asked for the expert method and to arrange the knowledge base is the task of consuming a long time (Liu, 2004). Setting PID parameters based on GA is a new way to search the best combination of PID parameters in the stable region of a system. The population optimizing mechanism of GA guarantees that the optimum solution or the optimum interval globally can be found without any initial information. According to the fitness function and the output situation of the controlled object, utilizing GA to set PID parameters is held within definitional domains of these parameters. Then the flexibility controllers are designed in accordance with the principle of flexibility model and five local controllers. Eventually, the nuclear reactor power control system is designed and simulated. The whole calculations and simulations are done in MATLAB.

2. LOCAL MODELS OF NUCLEAR REACTOR

Both the idea of flexibility model and the combination control strategy of the optimal control and the PID control are applied to the reactor from H.B. ROBINSON nuclear plant (Kerlin, et al., 1976). The reactor power is modeled using the point kinetics equations with six groups of delayed neutrons and reactivity feedbacks due to changes in fuel temperature and coolant temperature. The linearized equations are as follows

$$\frac{d\delta n_r}{dt} = -\frac{\beta}{\Lambda}\delta n_r + \sum_{i=1}^g \frac{\beta_i}{\Lambda}\delta c_{ri} + \frac{\rho_{r0}}{\Lambda}\delta r \quad (1)$$

$$\frac{d\delta c_{ri}}{dt} = \lambda_i \delta n_r - \lambda_i \delta c_{ri}, i = 1, 2, \dots, g \quad (2)$$

$$\begin{aligned} \frac{dT_f}{dt} = & \frac{f_f P}{m_f} \delta n_r - \frac{\Omega}{m_f} \delta T_f + \frac{\Omega}{2m_f} \delta T_i \\ & + \frac{\Omega}{2m_f} \delta T_e \end{aligned} \quad (3)$$

$$\begin{aligned} \frac{dT_c}{dt} = & \frac{(1-f_f)P}{m_c} \delta n_r + \frac{\Omega}{m_c} \delta T_f - \\ & \frac{2M+\Omega}{2m_c} \delta T_i + \frac{2M-\Omega}{2m_c} \delta T_e \end{aligned} \quad (4)$$

$$\delta r = \delta r_{rod} + a_f \delta T_f + \frac{a_c}{2} \delta T_i + \frac{a_c}{2} \delta T_e \quad (5)$$

Where, δ -the deviation of a parameter from initial steady-state value; n_r -normalized relative neutron density, m^{-3} ; Λ -neutron generation time, s; β -effective delayed neutron fraction; c_{ri} -ith group normalized precursor concentration, m^{-3} ; ρ -total reactivity; g -delayed neutron group number; λ_i -ith delayed neutron group decay constant, s^{-1} ; T_f -fuel average temperature, $^{\circ}C$; f_f -fuel power coefficient; P -reactor power, W; m_f -fuel total heat capacity, $J/^{\circ}C$; Ω -coefficient of heat transfer between fuel and coolant, $W/^{\circ}C$; T_i -coolant exit temperature, $^{\circ}C$; T_e -coolant inlet temperature, $^{\circ}C$; T_c -average temperature of coolant, $^{\circ}C$; m_c -total heat capacity of coolant, $J/^{\circ}C$; M -mass flow heat capacity, $W/^{\circ}C$; ρ_{rod} -reactivity due to control rod movement; a_c -coolant temperature coefficient of reactivity, $^{\circ}C^{-1}$; a_f -fuel temperature coefficient of reactivity, $^{\circ}C^{-1}$.

According to Eqs. (1), (2), (3), (4) and (5), the transfer function of the reactor power model from δn_r to $\delta \rho_{rod}$ can be calculated and represented by

$$G = \frac{dn_r}{dr_{rod}} = \frac{k \prod_{i=1}^3 (s - z_i)}{\prod_{i=1}^4 (s - p_i)} \quad (6)$$

Where, k -gain coefficient of the model; $z_i(i=1,2,3)$ -zeros of the model; $p_i(i=1,2,3,4)$ -poles of the model.

The transfer function model is both a LTI model and a four-order one. Linear transfer functions at five power levels 90%, 70%, 50%, 30% and 10% are expressed by G_1 , G_2 , G_3 , G_4 and G_5 in sequence and the five functions are used to denote the linear models at the five power levels. The models G_1 , G_2 , G_3 , G_4 and G_5 are treated as five local models of the reactor. Parameters of the five local models are given in Table 1.

3. LOCAL CONTROLLERS

Controllers of the five local models are designed respectively and seen as local controllers. The combination control strategy of an optimal controller and a PID controller is adopted as every local controller. Every optimal controller is first devised by using OCD and then contrive every PID controller to further improve the dynamic performances. Schematic of a local power control system is shown in Fig.1,

where $G_i(i=1,\dots,5)$ -a local model; $G_{OCi}(i=1,\dots,5)$ -an optimal controller corresponding to the model G_i ; $G_{PIDCi}(i=1,\dots,5)$ -a PID controller of the model $G_i * G_{OCi}$.

3.1 Optimal Control Base on MATLAB Toolbox

Devising an optimal controller based on the value optimal technique can be used to simply copy with the traditional optimal control problem via utilizing OCD in MATLAB, which has been adopted to design an optimal controller of a five-order linear model that is a single-input single-output (SISO) system, the PI controllers in series in a drive system of a direct-current machine being two closed loops, dynamic optimal controllers of a multi-input multi-output (MIMO) linear model and to calculate the optimal reduced-order model of a six-order linear model that is a SISO system (Xue, 2006). During carrying out this approach, Q and R are needless. The core of this toolbox is the optimal control program tracking the error index. In the process of operating the program, a user can utilize SIMULINK to build a control system model. In the model, the expression of the optimal controller to be designed can be optional and the controller is permitted having parameters to be optimized. After building a model in SIMULINK, designing the optimal controller is to optimize

Table 1 Parameters of the five local models

Model	k	z_1	z_2	z_3	p_1	p_2	p_3	p_4
G_1	56260	-2.116	-0.1754	-0.1501	-399.7	-1.999	-0.5491	-0.139800
G_2	43750	-2.121	-0.1861	-0.1506	-399.8	-2.070	-0.4313	-0.129800
G_3	31250	-2.127	-0.1989	-0.1499	-399.9	-2.091	-0.3000	-0.100300
G_4	31250	-2.132	-0.2126	-0.1495	-400.0	-2.119	-0.2410	-0.047310
G_5	31250	-2.138	-0.2267	-0.1496	-400.2	-2.136	-0.2294	-0.005856

Fig. 1 Schematic of a local power control system

these parameters of this controller via running the program.

3.2 PID Control Principle for Setting Parameters

The analog system consists of an analog PID controller and a controlled object, and the block diagram of a routine PID control system is shown in Fig.2, where $r(t)$ is the input; $y(t)$ is the output; $e(t)$ is the error; $u(t)$ is the control value.

In a digital control system, the incremental PID control expression is the following

$$\begin{aligned} \Delta u(k) &= u(k) - u(k-1) \\ &= K_p [e(k) - e(k-1)] + K_i * T e(k) \\ &\quad + \frac{K_d}{T} [e(k) - 2e(k-1) + e(k-2)] \end{aligned} \quad (7)$$

Where, T-sampling time; e(k)-the error value at kth sampling moment, k=0,1,2,...; u(k)-the control value at kth sampling moment;K_p-proportion coefficient; K_i-integration coefficient; K_d-differentiation coefficient.

In Eq. (7), K_p, K_i and K_d are three parameters to be setted via GA.

3.3 GA Used to Set PID Parameters

GA is the optimum method of searching parallel and randomly by simulating the genetic mechanism of the nature and biological evolution. The solution searched finally converges toward the global optimum direction. The key step of optimizing PID parameters is to define a decent fitness function (Krohling, 2001). To get satisfied dynamic performances in the transient process by minimizing an integral performance criterion (Zhuang, 1993), the time integral of the absolute value of e(t) is firstly adopted as the minimum objective function. To avoid the appearance of the

big control energy, the time integral of the quadratic term of u(t) is joined in this objective function. Then the time integral of the absolute value of ey(t) is added in the objective function to avoid the overshoot. Finally, the rise time is joined in the objective function to guarantee the rapid response of a system. The eventual objective function is the following

If $ey(t) < 0$,

$$J = \int_0^{\infty} (m_1|e(t)| + m_2u^2(t) + m_3|ey(t)|)dt + m_4t_u \quad (8)$$

Where, m_i(i=1,2,3,4)-weight coefficient which represents the important degree of the part multiplied by m_i in the eventual objective function; ey(t)= y(t) – y(t-1); t_u-the rise time.

The fitness function is the basis of the selection operation. Because optimizing PID parameters is to calculate the minimum value of the objective function and the maximum fitness value is needed during using GA, so the

Fig. 2 Block diagram of a routine PID control system

Table 2 Parameters of the five optimal controllers

	a	b ₁	b ₂	b ₃	c ₁	c ₂	c ₃	c ₄
G _{OC1}	0.39680	0.11451	1.20550	0.90994	0.22202	0.010514	0.039678	0.36610
G _{OC2}	0.86331	0.59919	0.82134	0.92199	0.50619	0.156140	0.076917	0.57649
G _{OC3}	0.88240	0.95620	0.55280	0.12430	0.02350	0.675800	0.326300	0.61200
G _{OC4}	0.68049	0.98262	0.30873	0.59784	0.23076	0.772450	0.260500	0.51392
G _{OC5}	0.69908	0.95974	0.34039	0.58527	0.22381	0.751270	0.255100	0.50596

issue of calculating the minimum value is changed into calculating the maximum fitness value, namely the objective function is converted into the fitness function. Therefore, the fitness function is represented by

$$F = 1 / J \quad (9)$$

3.4 Designing

Owing to the open loop transfer functions G_i(i=1,...,5) which are known, the five local power control system models are built separately in SIMULINK. ITAE is always selected as the performance index because it can make a

system enter the stable region rapidly when the index value is close to a small value. An optimal controller of every local model is designed via OCD and represented by

$$G_{OCi} = \frac{a \prod_{i=1}^3 (s + b_i)}{\prod_{i=1}^4 (s + c_i)} \quad (10)$$

Parameters of the five optimal controllers are shown in Table 2.

To set PID parameters of the five models G_i*G_{OCi}(i=1,...,5) rapidly and effectively, these models are

respectively reduced from a eight-order model to a two-order model via Schur method. First, set PID parameters of these two-order models via GA. After designing PID controllers of these two-order models, the satisfying controllers of the original models $G_i * G_{OCi} (i=1, \dots, 5)$ are finally gotten in turn by artificially and slightly regulating PID parameters of these two-order models to obtain better dynamic performances. They are denoted by $G_{PIDCi} (i=1, \dots, 5)$.

In the process of successfully writing and executing the GA program, the PID control arithmetic and the whole parameters are defined in turn. The input is the unit step signal and the incremental PID control arithmetic is selected. To reduce the computation load caused by selecting big value ranges of K_p , K_i and K_d , three decent value ranges are regulated via the trial method. The parameters are expressed by the ten place binary code form. According the optimizing situations, define the sampling time, the values of m_1 , m_2 , m_3 and m_4 , the individual number, the evolved generation number, the crossover probability and the mutation probability.

Adding a PID controller in every local model with only an optimal controller eliminates the overshoot and makes the output almost equal the defined input. Though the dynamic response speed is slower than one with only an optimal controller, it is accepted and satisfactory. Parameters of the five PID controllers are shown in Table 3.

Table 3 Parameters of the five PID controllers

	K_p	K_i	K_d
G_{PIDC1}	0.7820	0.0001	0.3519
G_{PIDC2}	1.0753	0.0001	0.2835
G_{PIDC3}	1.3690	0.0001	0.1857
G_{PIDC4}	7.2239	0.0001	0.5279
G_{PIDC5}	7.1065	0.0001	0.9971

$G_{PIDCi} (i=1, \dots, 5)$ designed is a PID controller of the model $G_i * G_{OCi} (i=1, \dots, 5)$ accordingly. After adding these PID controllers, when the inputs of the models $G_1 * G_{OC1}$, $G_2 * G_{OC2}$, $G_3 * G_{OC3}$, $G_4 * G_{OC4}$ and $G_5 * G_{OC5}$ are $0.01\beta (\beta=0.0064)$ step reactivity, step responses of δn_r from these models are shown in Fig.3. The response curve $C_i (i=1, \dots, 5)$ is the step response of δn_r of the model $G_i * G_{OCi} (i=1, \dots, 5)$ with a respective PID controller, $G_{PIDCi} (i=1, \dots, 5)$. As can be shown from these curves, this

combination control strategy can guarantee that every local power control system has good dynamic performances and works steadily. Therefore, both the way of contriving an optimal controller via OCD and the approach of designing a PID controller based on GA are rapid and effective.

Fig. 3 Step response $C_i (i=1, \dots, 5)$ of δn_r from the models $G_i * G_{OCi} (i=1, \dots, 5)$ with $G_{PIDCi} (i=1, \dots, 5)$ accordingly

4. NUCLEAR REACTOR POWER CONTROL SYSTEM

According to the local models and local controllers, design the nuclear reactor power control system by utilizing the idea of flexibility model developed in the paper and the system is used to cater to the whole power levels of the nuclear reactor.

4.1 Principle of Flexibility Model

The principle of flexibility model is to seek the unknown linear model at a random operating point via adopting known local linear models at different operating points of the real system which is usually nonlinear. This model sought is called a flexibility model. A simple schematic of a system is shown in Fig.4. The linear models of operating points "1" and "2" are known, and the others on segment "A" which spans from point "1" to point "2" are unknown, such as the random point "a". The principle of flexibility model can be applied to find the linear model at point "a" by using a decent function and the two known models. The decent function is performed by a membership function from Fuzzy Mathematics. A schematic of a simple membership function is shown in Fig.5, where M_i is the fuzzy set of i th point; x is the set of all points from "A", $a \in x$; μ is the membership and figures how point "a" belongs to M_i , its range is $[0, 1]$; the degree of overlap l is the length between intersection points x_1 and x_2 of the function and the lateral

axis, it denotes the set in which every point belongs to M_1 and M_2 simultaneously. According to Figs.4 and 5, one expression of finding the model at point “a” can be represented by

$$y_a = m_{M_1}(a)y_1 + m_{M_2}(a)y_2 \quad (11)$$

Where, y_a is the linear model corresponding to the random point “a”.

Fig. 4 Simple schematic of system

Fig. 5 Schematic of a type of membership function

The function of flexibility model is to exploit the set of flexibility models at different operating points of a nonlinear system to approximate the real system. In the difficult situation of modeling a nonlinear system, to model the flexibility model of the reactor via this principle is a new method for finally designing the nuclear reactor power control system.

4.2 Designing

In accordance with the principle of flexibility model, adopt a triangle membership function which is typical. The membership function of reactor models for whole levels is

shown in Fig.6.

The description of the i th rule R_i : if P is M_i then $Y_i = G_i (i=1,2,3,4,5)$, where R_i and P represent the i th fuzzy rule and a reactor power respectively; M_1, M_2, M_3, M_4 and M_5 separately represent the fuzzy sets corresponding to the power levels 90%, 70%, 50%, 30% and 10%; $\mu_{M_i}(P)$ represents the membership when the power P belongs to the fuzzy set of M_i , it can be calculated via a linear relationship between the membership and the reactor power; G_1, G_2, G_3, G_4 and G_5 represent local models corresponding to the five levels in sequence.

In Fig.6, values of four pair of intersection points of the function and the lateral axis are respectively $1760 \pm 0.5l, 1320 \pm 0.5l, 880 \pm 0.5l$ and $440 \pm 0.5l$. The memberships are unknown before defining the value l . The bigger l is, the worse the dynamic performances of a system are. l is too small, disturbances will be produced easily during switching among linear models. Given the two situations, l is chosen as 5. The global flexibility model expression can be represented by

$$G = \frac{\sum_{i=1}^5 m_{M_i}(P) \cdot G_i}{\sum_{i=1}^5 m_{M_i}(P)}, P \in (0, 2200] \quad (12)$$

The nuclear reactor power control system based on this flexibility model is constructed and its principle diagram is shown in Fig.7, where the controlled object is the reactor power flexibility model at a power level; FSM stands for fuzzy supervision mechanism which is used to produce weight value $w_i (i=1, \dots, 5)$ which denotes how i th local controller belongs to the power flexibility model, the expression of w_i is the following

$$w_i = \frac{m_{M_i}(P)}{\sum_{i=1}^5 m_{M_i}(P)}, i = 1, \dots, 5 \quad (13)$$

Fig. 6 Membership function of reactor models for whole power levels

Fig. 7 Principle diagram of nuclear reactor power control system

In Fig.7, the flexibility controller of the flexibility model is expressed by

$$G_{FC}(P) = \left(\sum_{i=1}^5 w_i G_{PIDi} \right) \times \left(\sum_{i=1}^5 w_i G_{OCi} \right), P \in (0, 2200] \quad (14)$$

Now the flexibility models and the flexibility controllers at the whole power levels of the reactor can be attained by Eqs. (12), (13) and (14) based on the five local models calculated and five local controllers designed. Both the flexibility model and the flexibility controller at a random power level compose a power control system at this power level. The combination of the power control system at every power level is to approximately carry out the power control of the nuclear reactor which is nonlinear.

5. SIMULATION

Without loss of generality, the nuclear reactor power control systems at the three typical power levels chosen optionally are simulated in turn. The power levels are the low power level 20%, the middle power level 60%, and the full power level 100%. According to Eqs. (12), (13) and (14), flexibility models and flexibility controllers corresponding to the levels are separately acquired. Then the power control systems of the flexibility models at 20%, 60% and 100% and

ones of the linearized models at these levels with still a respective flexibility controller are simulated in sequence. Finally, compare and analyse simulation results of the flexibility models and the linearized models.

Establish the practical simulation block diagram in SIMULINK shown in Fig.8, where the two parts of a PID controller and an optimal controller from a flexibility controller at a power level are expressed via the two subsystems encapsulated. When the signal of $\delta\rho_{rod}$ is 0.01β ($\beta=0.0064$) step reactivity, step responses of δn_r from the six models are shown in Figs. 9, 10 and 11, where the curves L1, L3 and L5 are the step responses of δn_r from the flexibility models at 20%, 60% and 100%, the curves L2, L4 and L6 are the step responses of δn_r from the linearized models at 20%, 60% and 100%. As can be seen from Figs. 9, 10 and 11, three pair of responses L1 and L2, L3 and L4, L5 and L6 are almost coincident and same respectively, which are also asymptotically stable. This simulation result shows that a flexibility controller at a random power level can guarantee satisfactory dynamic performances of the linearized power model at this level and this model can operate steadily, so the nuclear reactor power control system at a power level is effective for the linearized power model at this level.

According to the references (Li, 2008; Liu, 2002; Ziya

Fig. 8 Practical simulation block diagram in SIMULINK

Fig. 9 Step responses of δn_r of the flexibility model and the linearized model at a low power level 20%

Fig. 10 Step responses of δn_r of the flexibility model and the linearized model at a middle power level 60%

Fig. 11 Step responses of δn_r of the flexibility model and the linearized model at the full power level 100%

Akcasu, et al., 1971), it is gotten that the nonlinear degree of a nuclear reactor model based on lumped parameters can be so tolerant and accepted that the nuclear reactor model at a power level can be approximatively substituted by a linearized model of the nuclear reactor model at this power level, especially for a perturbation input. An example is the

reference (Li, 2008) in which the controller of the linearized power model at the full power level of a nuclear reactor model based on lumped parameters can guarantee good dynamic performances and the stability of the nonlinear reactor power model at this level. Therefore, the nuclear reactor power control system at a power level designed in this paper is valid for the reactor model at this power level.

6. CONCLUSION

A nuclear reactor nonlinear system is the object studied in this paper, the power control system of the nuclear reactor to guarantee that the reactor has good dynamic performances and can operate steadily at global power levels is designed. In the designing process, the idea of flexibility model is proposed and applied to deal with the nonlinear model problem of the reactor owing to the transformation of the power level of the reactor. Besides, the set of using OCD to devise an optimal controller and setting PID parameters via GA is a new try. The simulation result shows that the idea of flexibility model is functional to construct and improve the reactor linear model; this new try of designing a local controller is rapid and effective; the nuclear reactor power control system designed can achieve the objective of controlling the reactor power and is effective.

REFERENCES

- Adel Ben-Abdenmour, Robert M. Edwards and Kwang Y. Lee, 1992. "LQG/LTR Robust Control of Nuclear Reactors with Improved Temperature Performance". IEEE Transactions on Nuclear Science, 39(6), Dec., pp. 2286-2294.
- Bennett, S., 1993. "Development of the PID Controllers". IEEE Control Systems Magazine. 13(6), Dec., pp. 58-65.
- Liu, J., 2004. "Advanced PID Control and MATLAB Simulation", 2nd ed.. Publishing House of Electronics Industry, Beijing, Chap. 5, pp. 220-221 (in Chinese).
- Kerlin, T.W., Katz, E.M., Thakkar, J.G., and Strange, J.E., 1976. "Theoretical and Experimental Dynamic Analysis of the H.B. Robinson Nuclear Plant". Nuclear Technology, 30(3), Sep., pp. 299-316.
- Xue, d., 2006. "Computer Aided Control Systems Design Using MATLAB Language", 2nd ed.. Tsinghua University Press, Beijing, Chap. 6, pp. 284-305 (in Chinese).
- Krohling, R.A., and Rey, J.P., 2001. "Design of Optimal Disturbance Rejection PID Controllers Using Genetic Algorithms". IEEE Transactions on Evolutionary

Computation. 5(1), Feb., pp: 78-82.

Zhuang, M., and Atherton, D.P., 1993. "Automatic Tuning of Optimum PID Controllers". IEEE Proceedings of Part D, 140(3), May, pp: 216-224.

Li, h., 2008. "Application of Linearized Model to the Stability Analysis of the Pressurized Water Reactor". Nuclear Science and Engineering, 28(4), Dec., pp:341-346 (in Chinese).

Liu, b., 2002. "Modern control theory", 3rd ed.. China Machine Press, Beijing, Chap.4, pp: 157-185 (in Chinese).

Ziya Akcasu, Lellouche Gerald, S., and Shotkin Louis, M., 1971. "Mathematics Methods in Nuclear Reactor Dynamics". Academic Press, New York, Chap. 4-7, pp: 116-450.

Li, h., 2008. "Linearized Model for Optimal Controller Design of PWR Core and Its Application". Nuclear Power Engineering, 29(4), Aug., pp:84-87 (in Chinese).